

Quick Start Guide



THE ULTIMATE TIME MACHINE
..... For Complete Control



Certificate No.:SAA192515EA



Change Begins Here

Important - To ensure trouble free operation, please charge up your new Time-R in a wall socket for a minimum of two hours before use.

To Set The Clock

▲ or ▼ To Adjust Time
◀ or ▶ To Scroll

Press for 3 secs until the numbers flash.
Clock

Input current time
e.g. 06:00:00pm
Confirm

SWITCH 12/24 HRS

Press and hold CONFIRM, then press up arrow to choose AM/PM for 12hrs or blank for 24hrs
Confirm

TIMED MODE - up to 15 settings

ON OFF
▲ or ▼ To Adjust Time
◀ or ▶ To Scroll

Scroll to TIMED Mode
Mode

Input On & OFF Time for Group 1
e.g. 6:30am - 12:00pm
Confirm or For Next Group Setting

Confirm Once you have finished all groups setting

TIMED MODE - Display shown after programming

ON 06:30:00 AM Next On Time
OFF 12:00:00 PM Next OFF Time
06:00:00 AM Current Time
06:35:00 AM Starts Counting On Time
e.g. current time is 6:00am e.g. current time is 6:35am

Option: To Lock, Press Confirm 3 Times After Finished Setting

REPEAT MODE - from min 1 sec, up to 99hrs setting

ON H M S
OFF H M S
REPEAT

▲ or ▼ To Adjust Time
◀ or ▶ To Scroll

Scroll to REPEAT Mode
Mode

Input Repeat Cycle
e.g. 15 secs ON for every 1 hour
Confirm

REPEAT MODE - Display Shown After Programming

ON 00:00:15 Starts Counting ON Time
OFF 00:59:45 Starts Counting OFF Time
After 15 Secs ON

Option: To Lock, Press Confirm 3 Times After Finished Setting

COMBINED MODE - Up To 3 Group Settings

ON 00:00:00
OFF 00:00:00
Group 1
COMBINED

▲ or ▼ To Adjust Time
◀ or ▶ To Scroll

06:00:00 AM
12:00:00 PM
COMBINED
Input Time Cycle
e.g. 6:00am - 12:00pm
15secs on every 1 hr.

For Group 1 Cycle Setting

COMBINED MODE - Display Shown After Programming

06:00:00 AM
05:30:00 AM
COMBINED
e.g. Current Time Is 5:30am

00:00:15
00:59:45
COMBINED
When It Is 6:00am

Next On Time
Current Time
Starts Counting ON time, then OFF time

Scroll to COMBINED Mode
Mode

ON H M S
OFF H M S
COMBINED

00:00:15
00:59:45
COMBINED
Input Repeat Cycle

Confirm or For Next Group Setting

Option: To Lock, Press Confirm 3 Times After Finished Setting


MANUAL ON and OFF MODE

Manual OFF: press CLOCK 5 times

Manual ON: press CLEAR 5 times

What is Lock Function?

To prevent accidental adjustment, there is a lock option. To lock, press CONFIRM 3 times after finished setting. It only freezes the MODE button, other buttons will still function. To unlock, press CONFIRM 3 times



HOW TO CHECK:

When TIME-R is in operation, press CHECK once, then press right arrow to move to the page of each setting. Press CHECK again to return to current operation

HOW TO CLEAR:

1. During setting, press CLEAR once to erase the whole page, dashes appear

2. Press CONFIRM to erase the setting or CLEAR again to return to the previous setting

HOW TO CHECK CURRENT TIME:

During operation, press CLOCK once to check current time

PRECAUTIONS:

1. Please always keep the timer indoors and in dry place whether it's in operation or not
2. Do not use with power extension cords
3. Always operate the timer with equipment NOT exceeding the rated current
4. Please always check and recharge the battery before using
5. Do not open the timer under any circumstances or try to fix it by yourself

RATED CURRENT:

ALWAYS OPERATE THE TIMER WITH EQUIPMENT NOT EXCEEDING THE RATED CURRENT

Rated Current

UK 13A (220 - 240V 50Hz) / AU 10A (220 - 240V 50Hz) / EU 16A (220 - 240V 50Hz) / US 15A (110 - 120V 50Hz)